SD101A (1N6263)...SD101C


SILICON SCHOTTKY BARRIER DIODES

for general purpose applications

The SD101 Series is a metal on silicon Schottky barrier device which is protected by a PN junction guard ring. The low forward voltage drop and fast switching make it ideal for protection of MOS devices, steering, biasing and coupling diodes for fast switching and low logic level applications.

The SD101A is equivalent to the 1N6263.

This diode is also available in MiniMELF case with type designation LL101A, B, C.



Glass Case DO-35 Dimensions in mm

Absolute Maximum Ratings ($T_a = 25 \, ^{\circ}$ C)

Parameter		Symbol	Value	Unit	
Peak Reverse Voltage	SD101A SD101B SD101C	V_{RRM}	60 50 40	V	
Power Dissipation		P _{tot}	400 ¹⁾	mW	
Maximum Single Cycle Surge, 10 s Square wave		I _{FSM}	2	А	
Junction Temperature		T _j	200	°C	
Storage Temperature Range		Ts	- 55 to + 200	°C	
1) Valid provided the leads direct at the cas	se are kept at ambie				

Characteristics at T_a = 25 °C

Parameter		Symbol	Min.	Max.	Unit
Reverse Breakdown Voltage					
at I _R = 10 μA	SD101A		60	-	
·	SD101B	$V_{(BR)R}$	50	-	V
	SD101C		40	-	
Forward Voltage					
at I _F = 1 mA	SD101A		-	0.41	
	SD101B		-	0.4	
	SD101C	V_{F}	-	0.39	V
at I _F = 15 mA	SD101A		-	1	
	SD101B		-	0.95	
	SD101C		-	0.9	
Reverse Leakage Current					
at $V_R = 50 \text{ V}$	SD101A			200	A
at $V_R = 40 \text{ V}$	SD101B	I_R	-	200	nA
at $V_R = 30 \text{ V}$	SD101C				
Junction Capacitance					
at $V_R = 0 V$, $f = 1 MHz$	SD101A	0	-	2	~F
	SD101B	C_{tot}	-	2.1	pF
	SD101C		-	2.2	
Reverse Recovery Time		+		1	ne
at $I_F = I_R = 5 \text{ mA}$, recover to 0.1 I_R		t _{rr}	_	'	ns



SEMTECH ELECTRONICS LTD.


(Subsidiary of Sino-Tech International Holdings Limited, a company listed on the Hong Kong Stock Exchange, Stock Code: 724)










Dated: 23/06/2007











SEMTECH ELECTRONICS LTD.

(Subsidiary of Sino-Tech International Holdings Limited, a company listed on the Hong Kong Stock Exchange, Stock Code: 724)





