


ST 2N5088 / 2N5089

NPN Silicon Epitaxial Planar Transistor

for switching and AF amplifier applications.

The transistor is subdivided into one group according to its DC current gain. As complementary type the PNP transistor 2N5086 and 2N5087 are recommended.




1. Emitter 2. Base 3. Collector
TO-92 Plastic Package

Absolute Maximum Ratings ($T_a = 25\text{ }^\circ\text{C}$)

Parameter	Symbol	Value	Unit
Collector Base Voltage	V_{CBO}	35	V
Collector Emitter Voltage	V_{CEO}	30	V
Emitter Base Voltage	V_{EBO}	4.5	V
Collector Current	I_C	50	mA
Power Dissipation	P_{tot}	500	mW
Junction Temperature	T_j	150	$^\circ\text{C}$
Storage Temperature Range	T_{stg}	- 55 to + 150	$^\circ\text{C}$







Characteristics at $T_a = 25\text{ }^\circ\text{C}$

Parameter	Symbol	Min.	Max.	Unit	
DC Current Gain at $V_{CE} = 5\text{ V}$, $I_C = 0.1\text{ mA}$ at $V_{CE} = 5\text{ V}$, $I_C = 1\text{ mA}$ at $V_{CE} = 5\text{ V}$, $I_C = 10\text{ mA}$	2N5088	h_{FE}	300	900	-
	2N5089	h_{FE}	400	1200	-
	2N5088	h_{FE}	300	-	-
	2N5089	h_{FE}	400	-	-
	2N5088	h_{FE}	300	-	-
	2N5089	h_{FE}	400	-	-
Collector Base Cutoff Current at $V_{CB} = 35\text{ V}$	I_{CBO}	-	50	nA	
Emitter Base Cutoff Current at $V_{EB} = 4.5\text{ V}$	I_{EBO}	-	50	nA	
Collector Base Breakdown Voltage at $I_C = 100\text{ }\mu\text{A}$	$V_{(BR)CBO}$	35	-	V	
Collector Emitter Breakdown Voltage at $I_C = 1\text{ mA}$	$V_{(BR)CEO}$	30	-	V	
Emitter Base Breakdown Voltage at $I_E = 10\text{ }\mu\text{A}$	$V_{(BR)EBO}$	4.5	-	V	
Collector Emitter Saturation Voltage at $I_C = 10\text{ mA}$, $I_B = 1\text{ mA}$	$V_{CE(sat)}$	-	0.5	V	
Base Emitter Voltage at $V_{CE} = 5\text{ V}$, $I_C = 10\text{ mA}$	$V_{BE(on)}$	-	0.8	V	
Gain Bandwidth Product at $V_{CE} = 5\text{ V}$, $I_C = 0.5\text{ mA}$	f_T	50	-	MHz	
Collector Output Capacitance at $V_{CB} = 10\text{ V}$, $f = 1\text{ MHz}$	C_{ob}	-	4	pF	










SEMTECH ELECTRONICS LTD.
Subsidiary of Sino-Tech International (BVI) Limited













SEMTECH ELECTRONICS LTD.
Subsidiary of Sino-Tech International (BVI) Limited





SEMTECH ELECTRONICS LTD.
Subsidiary of Sino-Tech International (BVI) Limited





SEMTECH ELECTRONICS LTD.
 Subsidiary of Sino-Tech International (BVI) Limited

